

EHN26-P

C-style Earpiece with In-line PTT and Microphone (Black) -- for HP5, HP6, HP7, PD6, X1 series and PDC550, PDC680, PDM680, PTC680, Z1p, PT590

C-style earpiece with in-line PTT and microphone to be used with handheld radios in PD6 and X1 series.
With an integrated chip for verification as an original Hytera accessory.

- Perfect fit and pleasant wearing comfort
- In-ear and swivel design so it can be worn in either ear
- Economical and practical design to meet customers' needs
- PTT inline wire control structure
- Plastic cable clamp for PTT position adjustment

Specifications

Weight: about 35g

Colour: black

PTT key: available

PTT cycles: $\geq 100,000$

VOX: YES (activation in conjunction with the radio's VOX function)

Emergency key: none

Radio connector: 13-pin connector

Microphone sensitivity: -42 ± 3 dB @1kHz 2.0V 2.2K Ω ; 0dB=1V/Pa

Speaker power: 10 mW (rated); 30 mW (max.)

Speaker impedance: $32 \Omega \pm 15\%$ @1kHz

Speaker frequency response: 100 ± 3 dB @1kHz at 0.179V

Speaker sensitivity: 105 ± 3 dB @ 1 kHz

Ingress protection: none

Operating temperature: -20°C to 60°C

Storage temperature: -40°C to 85°C

Suitable radios: HP505, HP565, HP605, HP685, HP705, HP785, PDC550, PDC680, PDM680, PTC680, PD605, PD665, PD685, X1e, X1p, Z1p, PT590